

PEDAL PUSHER mini



Line powered version.



Dante Option P0E powered.

Dual mono Console/DAW to Guitar Pedal Interface

- Each channel features:
 - High headroom line level balanced input to efx pedal send with impedance and level matching.
 - High impedance guitar pedal return to high headroom line level balanced output.
 - Selectable pickup simulation, Active or Passive.
 - High frequency equalizer in the passive position to simulate or negate the effect of guitar cable.
- Low noise universal power supply built in, no wall wart!
- Pedal Returns can also function as high quality, dual mono or stereo, high impedance, direct instrument inputs (DI) with line level outputs. Each return has two gain settings.
- Pedal Sends can serve as high quality outputs from a console/DAW to a guitar amp for re-amp use.
- Routing switches add flexibility for feeding both loops from one input or both outputs from one Pedal return. For example: feed two different pedal loops from a single line input or feed a clean and effected signal to the console from a guitar input.
- DANTE option allow connection to Dante network at sample rates up to 96k. Power is supplied via P0E (power over ethernet) or from external power supply. Dante and analog outputs are mirrored. Inputs are selectable from Dante or analog.

AudioSimplified

Pedal Pusher Mini Specs:

Line Inputs:

Nominal Level : +4dBu

Maximum Input level: +24dBu

Impedance: 48k Ω differential

Line Outputs:

Nominal Level : +4dBu

Maximum Balanced Output level: +27.5dBm into 600 Ω

Maximum UnBalanced Output level: +22dBm into 600 Ω

Frequency Response: 20Hz to 20kHz +0.02dB, -0.12dB

Noise level:

-101.3 dBa

Distortion:

THD: .00114%

IMD: .00278%

Power Mains version:

Voltage Range: 80-246vac (universal power)

Frequency Range: 47-63Hz

A/C Current: .25A @115VAC

Power Dante version:

POE: 3.8w, class 0

External: 48v, 150ma, 1500v ISO certified

Dimensions:

width: 8.15" (207mm)

height: 1.75" (42mm)

depth: 4" (100mm)

Dante Option:

Sample Rates: All standard up to 96k

Ports: (1)POE/Dante, (1)Dante for daisy chain

Outputs: Dante and analog simultaneously

Inputs: Dante or analog switchable

Price:

Pedal Pusher Mini: \$270.00

Pedal Pusher Mini with Dante: \$420.00

©2021 Audio Simplified LLC, Jim Mikles
6401 Hickory Overlook, Columbia, MD 21044
audio-simplified.com 410.999.0918